




27" inch Embedded Touch Monitor (Pure Flat Project Capacitive Multi-Touch)

Products application :

- POS Terminal
- Industrial PC
- Kiosk
- Gaming
- Medical apparatus
- Personal computer
- Mobile GPS
- Office automation
- Security system of the house
- Car-mounted amusement
- Military equipment
- Communicate



27" inch Embedded Touch Monitor (Pure Flat Project Capacitive Multi-Touch)

Display Specifications :

Active Area	597 × 336 mm
Pixel Pitch	0.31125 × 0.31125 mm
Brightness	300 cd/m ²
Contrast Ratio	3000 : 1
Resolution	1920 x 1080 (Full HD)
Viewing Angle	左右 178° ; 上下 178°
Response Time	12 ms (Tr + Tf)
Display Colors	16.7M
Display Modes	640×480 ; 800×600 ; 1024×768 ; 1280×720 ; 1280×800 ; 1280×1024 ; 1366×768 ; 1440×900 ; 1680×1050 ; 1920×1080
Signal input	VGA ; Audio ; DVI
Mini-Audio out	1W (8Ω) ×2
OSD Keyboard	⊙ Menu/Select ⊙ - ⊙ + ⊙ Auto/Exit ⊙ Power
Power Source 、 Power Consumption	DC 12V ; ≤25w ; Standby ≤1w
Storage 、 Operation	-20~60℃ 、 0~50℃
VESA	100×100 or 200×100 mm
Casing Colors	Black
Casing Size 、 Weight	684.28 × 394.7 × 46 mm ; 9.3 kg (W×H×D)
Carton 、 gross weight	730 × 560 × 300 mm ; 11.8 kg (W×H×D)



Touch Feature :

Input Method	Capacitive stylus, Finger
Linearity	≤2.5mm
Surface	≥7H
Life Time	Unlimited
Application	Writing and Signature Capture Capability
PC Link	USB

Software Feature :

Draw Test	Position and linearity verification
Controller	Support multiple controllers
Languages	English 、 Simple Chinese 、 Traditional Chinese 、 Japanese 、 French 、 German 、 Spanish 、 Korean 、 Arabic 、 Czech 、 Danish 、 Dutch 、 Greek 、 Hungarian 、 Italian 、 Norwegian 、 Russian 、 Polish 、 Portuguese 、 Slovenian 、 Swedish 、 Thai 、 Turkish
Mouse Emulator	Right / left button emulation. Auto Right / left Click (PDA function)
Touch Style	Drawing a Mode 、 button a Mode 、 Touch Off/ on Switch
Double Click	Configurable double click speed 、 Configurable double click area
Sound Modes	No sound 、 Touch down 、 Touch up
Display Support	display rotation 、 Support multiple monitors
Division Pattern Settings:	Support two halves and four parts with touch function, you can also create your own division patterns.
Edge compensation Support O.S	Support edge compensation and you can also add your own numbers for it. All Windows-32 bit O.S Windows7-8-10 : XP-64 bit O.S Android : All Linux : MAC



Order Information :

AIM-TMOPPCT270-R03W : Accessory	【VGA/AUDIO/DVI/USB-TOUCH】 VGA Cable / Audio Cable / Power Cable / AC90~260V Adapter / USB or RS232 Cable / Cleaning wipes/Driver Disk ※DVI Cable(Optional)	AIM-TMOPPCT270-R04W : Accessory	【VGA/AUDIO/DVI/RS232-TOUCH】 VGA Cable / Audio Cable / Power Cable / AC90~260V Adapter / USB or RS232 Cable / Cleaning wipes/Driver Disk
------------------------------------	--	------------------------------------	---



3 Year Warranty
LCD Panel 1 Year



